

**Roll No:** 

#### **BTECH**

(SEM VI) THEORY EXAMINATION 2023-24

### **CONTROL SYSTEM**

#### TIME: 3 HRS

**M.MARKS: 100** 

Note: 1. Attempt all Sections. If require any missing data; then choose suitably.

	SECTION A			
1.	Attempt <i>all</i> questions in brief.	2 x 10	= 20	_
Q no.	Question	Marks	СО	
a.	What is the difference between an open and closed loop system?	2	1	
b.	In most of the cases, disturbances are introduced in process in closed loop control system. Why?	2	1	
c.	What are the conditions for a system to be controllable?	2	2	
d.	What are the advantages of state-space model over transfer function?	2	2	
e.	What is the advantage of calculating overshoot control system?	2	3	
f.	What is the difference between fall time and rise time?	2	3	
g.	How location of poles is related to stability?	2	4	
h.	How is departure angle measured?	2	4	0
i.	What is the significance of gain and phase margin?	2	5	sit
j.	What is the significance of polar coordinates	2	5	
2.	SECTION B Attempt any <i>three</i> of the following:	6	20	レ
a.	Obtain the Transfer function of the given block diagram	10	1	

#### **SECTION B**

#### Attempt any *three* of the following: 2.





Subject Code: KEC602

**Roll No:** 

# BTECH

(SEM VI) THEORY EXAMINATION 2023-24

#### CONTROL SYSTEM

#### TIME: 3 HRS

**M.MARKS: 100** 

с.	The open loop transfer function of a unity feedback system is given by	10	3
	$G(S) = \frac{K}{S(1+ST)}$		
	Where 'K' & 'T' are positive constants. By what factor should the amplifier gain be reduced so that the peak overshoot of unit step response of the system is reduced from 75% to 25%.		
d.	Using Routh Hurwitz Criterion, discuss the stability of the characteristic equation: $2s^5 + 2s^4 + s^3 + 2s^2 + 2$	10	4
e.	What is gain margin, phase margin, gain crossover frequency, and phase cross frequency? What is the practical use of these parameters?	10	5

## **SECTION C**

### 3. Attempt any *one* part of the following:

	Therein per uny one part of the following.			
a.	Construct the signal flow graph for the following set of simultaneous	10	1	al
	equations and obtain the overall transfer function using Mason's gain			N
	formula.		. (	
	X2 = A21X1 + A23X3		V	
	X3 = A31X1 + A32X2 + A33X3	3	•	
	X4 = A42X2 + A43X3	1.2		
b.	Reduce the block diagram to its canonical form and obtain C(S)/R(S).	10	1	
	$ \begin{array}{c} & & & & & \\ & & & & \\ & & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & & \\ & & & \\ & & & \\ & & & \\ & & & & & \\ & & $			

4. Attempt any one part of the following: a. For a single input system  $\dot{X} = AX + BU$  Y = CX  $A = \begin{bmatrix} 0 & 1 \\ -1 & -2 \end{bmatrix}; B = \begin{bmatrix} 0 \\ 1 \end{bmatrix}; C = \begin{bmatrix} 1 & 1 \end{bmatrix}$ Check the controllability & observability of the system. b. Examine the Controllability and Observability of the following system:  $A - \begin{bmatrix} 0 & 1 & 0 \\ 0 & 0 & 1 \\ -6 & -11 & -6 \end{bmatrix} B - \begin{bmatrix} 1 \\ 0 \\ 1 \end{bmatrix} C - \begin{bmatrix} 10 & 5 & 1 \end{bmatrix}$ 

**2 |** P a g e





Roll No:

**BTECH** 

(SEM VI) THEORY EXAMINATION 2023-24

#### **CONTROL SYSTEM**

TIME: 3 HRS

**M.MARKS: 100** 

5.	Attempt any one part of the following:			
a.	Consider a standard second order system given by	10	3	
	$an^2$			
	$w_n$			
	$s^2{+}2\zeta w_ns{+}w_n^2$			
	The correlation between the maximum peak overshoot in the time domain			
	and the resonant peak in the frequency domain exists when:			
b.	The output of a standard second-order system for a unit-step input is	10	3	
	given as			
	$y(t)=1-rac{2}{\sqrt{3}}e^{-t}\cos\left(\sqrt{3}t-rac{\pi}{6} ight)$			
	What is the transfer function of the system?			6
6.	Attempt any <i>one</i> part of the following:		C	, Yo
a.	Using Routh Hurwitz Criterion, discuss the stability of the characteristic	10	4	V
	equation:			
	$F(s) = 2s^5 + 3s^4 + 2s^3 + s^2 + 2s + 2$	رنى	•	
b.	Consider a unity-feedback control system with the following	10	4	
	feedforward transfer function:			
	K K			
	$G(s) = \frac{1}{s(s+1)(s+2)}$			
	Draw plot the root locus.			
	<u>്</u> .	<u>.</u>	. <u> </u>	
7.	Attempt any <i>one</i> part of the following:			

C(a) =	K
G(S) =	s(s+1)(s+2)
Draw plot th	e root locus.

a. Sketch the Bode Plot for the given system and comment on stability of the used 10 systems: $G(s)H(s) = \frac{4}{s(1+0.5s)(1+0.08s)}$	
systems: $G(s)H(s) = \frac{4}{s(1+0.5s)(1+0.08s)}$	5
$G(s)H(s) = \frac{4}{s(1+0.5s)(1+0.08s)}$	
s(1+0.5s)(1+0.08s)	
b. Construct the Bode plots for a unity feedback system whose open-loop 10	5
transfer function is given by $[0.25(1+0.5s)]/[s(1+2s)(1+4s)]$ .	
From the Bode plot, determine the following:	
a) Gain and phase crossover frequencies,	
b) Gain and phase margin, and	
c) Comment on the stability of the system.	